



Instruction Manual
Historiador Cronógrafo Estoril

Historiador

Cronógrafo Estoril

Functions

Hours, minutes, small seconds, tachymeter, telemeter and chronograph. Date display at 6h.

Starting the Watch

If the watch has stopped, a few turns of the crown (pos.1) clockwise are sufficient to restart it. When worn, the natural wrist movement will be sufficient to keep the charge.

Handling and Corrections

- Pull the crown to the point of resistance (position 2) to stop the watch, then rotate the crown counterclockwise to set the time.
- Push button A : Starting and stopping the chronograph.
- Push button B : Reset the chronograph, only after stopping the timing with the push-button A. Use the chronograph function only with the crown closed.
- With the help of a pointed object, press the date pusher for as many times as needed to reset the date.

Warning

Set the time only when he chronograph is 0.
Do not fix the date when the hands are between 09:00 P.M. and 00:30.

Maintenance

To ensure a service that meets the brand's standards, any servicing of your watch must be carried out by Cuervo y Sobrinos customer service or an approved watchmaker. Whenever repairs are made during the warranty period, you must present the proof of warranty, with the date and name of the retailer where the watch was purchased.

- A - Minutes hand
- B - Date pusher
- C - Hours hand
- D - Seconds hand
- E - Seconds hand (chronograph)
- F - Push-button A: start/stop of chronograph
- G - Minutes hand (chronograph)
- H - Crown
- I - Hours hand (chronograph)
- L - Push-button B: return to zero of chronograph
- M - Date display



